

DIODE List > Small Signal Schottky

PartNo. (勾通方式)	VRM(VR) (V) (Range)	I _o (mA) (Range)	I _{FSM} (mA)	VFM Rating MAX.(V) (Range)	V _{FM} Conditions I _f (mA)	IRM(IR) Rating MAX.(μA)	IRM(IR) Conditions VR(V)	C _b (pF)	@V _R /Freq. (V/MHz)
BAT42VS	30	200	400	1	200	0.5	25	7	1/1
BAS85	30	200	5000	0.8	100	2	25	10	1/1
RB520S40	40	250	1000	0.6	200	5	30	50typ.	0/1
SD103AW	40	350	1500	0.6	200	5	30	50typ.	0/1
SD103AWS	40	350	1500	0.6	200	5	30	50typ.	0/1
RB520S30	30	200	1000	0.6	200	1	10	-	-
RB521S30	30	200	1000	0.5	200	30	10	-	-
SS0540Y	40	500	5500	0.62	1000	10	20	78	1/1
USB06U4SD	32	1000	5000	0.31	100	50	30	150	0/1
BAT42VS	30	200	400	1	200	0.5	25	7typ.	1/1
BAT54WS	30	200	600	0.8	100	2	25	10	1/1
BAT54TS	30	200	600	0.8	100	2	25	-	-
BAT54	30	200	600	0.8	100	2	25	10	1/1
BAT54A	30	200	600	0.8	100	2	25	10	1/1
BAT54C	30	200	600	0.8	100	2	25	10	1/1
BAT54S	30	200	600	0.8	100	2	25	10	1/1
BAT54W	30	200	600	0.8	100	2	25	10	1/1
BAT54AW	30	200	600	0.8	100	2	25	10	1/1
BAT54CW	30	200	600	0.8	100	2	25	10	1/1
BAT54SW	30	200	600	0.8	100	2	25	10	1/1
BAT54TB	30	200	600	0.8	100	2	25	10	1/1
BAT54ATB	30	200	600	0.8	100	2	25	10	1/1
BAT54CTB	30	200	600	0.8	100	2	25	10	1/1
BAT54ADW	30	200	600	0.8	100	2	25	10	1/1
BAT54CDW	30	200	600	0.8	100	2	25	10	1/1

BAT54SDW	30	200	600	0.8	100	2	25	10	1/1
BAT54DW	30	200	600	0.8	100	2	25	10	1/1
BAT54STB	30	200	600	0.8	100	2	25	10	1/1
BAT54TDW	30	200	600	1	100	2	25	10	1/1
RB751V40	40	30	200	0.37	1	0.5	30	2typ.	1/1
RB751S30*	-	-	-	-	-	-	-	-	-
BAS40	40	120	200	1	40	1	30	5	0/1
BAT721	40	200	1000	0.55	200	15	30	50	0/1
BAT721A	40	200	1000	0.55	200	15	30	50	0/1
BAT721C	40	200	1000	0.55	200	15	30	50	0/1
RB751V40	40	30	200	0.37	1	0.5	30	2typ.	1/1
RB501V-40	45	100	1000	0.55	100	10	10	6typ.	10/1
BAS70	70	70	-	1	15	0.1	50	2	0/1
BAS70A	70	70	-	1	15	0.1	50	2	0/1
BAS70C	70	70	-	1	15	0.1	50	2	0/1
BAS70S	70	70	-	1	15	0.1	50	2	0/1
BAS70W	70	70	-	1	15	0.2	50	2	0/1
BAS70AW	70	70	-	1	15	0.2	50	2	0/1
BAS70CW	70	70	-	1	15	0.2	50	2	0/1
BAS70SW	70	70	-	1	15	0.2	50	2	0/1
BAS70TW	70	70	-	1	15	0.2	50	2	0/1
BAT64A	40	120	800	0.75	100	2	30		
BAS316	85	250	500	1.25	150	1	75	1.5	

Package (勾选方式)
SOD-123
LL-34
SOD-523
SOD-123 SOD-523
SOD-323
SOD-523
SOD-523 SOD-723
SOD-123
SOT-353
SOD-123
SOD-323
SOD-523
SOT-23
SOT-23
SOT-23
SOT-23
SOT-323
SOT-323
SOT-323
SOT-323
SOT-523
SOT-523
SOT-523
SOT-363
SOT-363

SOT-363
SOT-363
SOT-523
SOT-363
SOD-323 SOD-523
-
SOT-23
SOT-23
SOT-23
SOT-23
SOD-323 SOD-523
SOD-323
SOT-23 SOT-23-3
SOT-23 SOT-23-3
SOT-23 SOT-23-3
SOT-23 SOT-23-3
SOT-323
SOT-323
SOT-323
SOT-323
SOT-323
SOT-23
SOD-323 SOD-323F SOD-523

DIODE List > General Purpose Diode

PartNumber (构造方式)	Description (构造方式)	I _o (A) (Range)	V _{RM} (VR) (V) (Range)	I _{FSM} (A)	V _{FM} Rating MAX.(V) (Range)	V _{RM} Conditions IF(A)	IRM(IR) Rating MAX.(μA)	IRM(IR) Conditions VR(V)	t _{rr} (ns) Rating MAX.(ns) (Range)	t _{rr} (ns) Conditions IF(A) (Range)	Package (构造方式)
ES1A	SuperFast	1	50	30	0.95	1	5	50	35	0.5	SMA SOD-123F
RS1A	Fast	1	50	30	1.3	1	5	50	150	0.5	SMA DO-41
IN5401G	Glass-passivated	3	100	200	1.2	3	5	100	-	-	DO-201AD
ES1B	SuperFast	1	100	30	0.95	1	5	100	35	0.5	SMA SOD-123F
RS1B	Fast	1	100	30	1.3	1	5	100	150	0.5	SMA DO-41
ES1C	SuperFast	1	150	30	0.95	1	5	150	35	0.5	SMA SOD-123F
ES1D	SuperFast	1	200	30	0.95	1	5	200	35	0.5	SMA SOD-123F
ES2D	SuperFast	2	200	60	0.95	2	5	200	35	0.5	SMB
UMR2520	SuperFast	25	200	500	0.95	25	10	200	50	0.5	TO-220-2
US1D	UltraFast	1	200	30	1	1	5	200	50	0.5	SMA
UMR1020C	UltraFast	5	200	50	1.2	5	50	200	45	1	TO-220 TO-220F
UMR820	UltraFast	8	200	100	0.975	8	5	200	58	1	TO-220-2
UMR2020	UltraFast	20	200	250	1.1	20	50	200	75	1	TO-220-2
SFR1020C	UltraFast	10	200	50	0.9	5	50	200	40	0.5	TO-220 TO-220F
FCI200C20C	UltraFast	20	200	120	1.08	10	25	200	31	10	TO-220F TO-220F-2
UA60UP20	UltraFast	60	200	120	1.5	30	100	200	45	1	TO-247F TO-247F-2
UHR0620	HyperFast	6	200	70	1.5	6	100	200	55(Typ)	6	TO-220 TO-220F
UHR1020	HyperFast	10	200	120	1.5	10	100	200	52(Typ)	10	TO-220 TO-220F
UHR3020C	HyperFast	30	200	160	1.05	15	10	200	40	1	TO-220
RS1002FL	Fast	1	200	30	1.3	1	1	200	150	0.5	SOD-123F
RS1D	Fast	1	200	30	1.3	1	5	200	150	0.5	SMA DO-41
BW23x	UltraFast	0.4	250	9	1	0.1	0.1	200	50	0.03	SOT-23
HER504G	Glass-passivated	5	300	200	1	5	10	300	50	0.5	DO-201AD
ES1E	SuperFast	1	300	30	1.25	1	5	300	35	0.5	SMA SOD-123F
UMR2030C	SuperFast	10	300	105	1.4	10	10	300			TO-220
UMR6030C	SuperFast	30	300	164	1.4	30	10	300	42	1	TO-247
UR3030C	UltraFast	30	300	125	1.5	15	10	300	35	0.5	TO-220 TO-220F
FCI200C30C	UltraFast	20	300	120	1.3	10	25	300	95	10	TO-220F TO-220F-2
UA60UP30	UltraFast	60	300	200	1.5	30	100	300	55	30	TO-3PB TO-247F-2
UFR6030C	UltraFast	60	300	180	1.25	30	1	300	50	30	TO-3P TO-220-2
UFR8030C	UltraFast	80	300	370	1.8	80	1	300	75	30	TO-247 TO-3P
UFR10030C	UltraFast	100	300	300	1.25	50	1	300	80	30	TO-247 TO-3P
FR104G	Glass-passivated	1	400	30	1.3	1	5	400	150	0.5	DO-41
IN4004G	Glass-passivated	1	400	30	1.1	1	5	400	-	-	DO-41 SMA SOD-123F
SP26G	Glass-passivated	2	400	50	1.3	2	5	400	35	0.5	DO-15
SP36G	Glass-passivated	3	400	100	1.25	3	5	400	35	0.5	DO-201AD
SP56G	Glass-passivated	5	400	150	1.25	5	5	400	35	0.5	DO-201AD
ES1G	SuperFast	1	400	30	1.25	1	5	400	35	0.5	SMA SOD-123F
DSE804	SuperFast	8	400	125	1.3	8	1	400	50	0.5	TO-220F TO-220F-2
ER1004	SuperFast	10	400	110	1.5	10	10	400	60	5	TO-220F-2 TO-220F
UFR10040	SuperFast	75	400	500	1.7	75	100	400	80	30	TO-247
ER1004C	SuperFast	10	400	150	1.3	10	10	400	50	5	TO-220 TO-220F
UA60UP40	SuperFast	30	400	210	1.7	30	100	400	50	1	TO-3PB TO-247
UMR2040C	SuperFast	20	400	105	1.5	10	10	400	60	1	TO-220 TO-3PF
UMR1040C	UltraFast	5	400	48	1.4	5	10	400	50	1	TO-220
UMR840	UltraFast	8	400	100	1.5	8	5	400	50	1	TO-220-2
UR1540	UltraFast	15	400	200	1.25	15	100	400	60	15	TO-220-2
UFR9040C	UltraFast	90	400	230	1.3	45	1	400	55(typ)	30	TO-220F-2 TO-247
UFR6040C	UltraFast	60	400	180	1.5	30	1	400	50	30	TO-3P TO-247
UA60UP40	UltraFast	60	400	210	1.7	30	100	400	70	30	TO-3P TO-247S
UD80040	UltraFast	80	400	300	1.5	40	10	400	108(Typ)	1	TO-3P
UFR8040	UltraFast	40	400	120	1.9	40	10	400	35(Typ)	1	TO-3P
UFR8040C	UltraFast	80	400	400	1.8	40	10	400	40	20	TO-220-2 TO-247 TO-3P
UFR10040C	UltraFast	100	400	300	1.5	50	1	400	70	30	TO-247 TO-3P
UFR12040C	UltraFast	120	400	360	1.5	60	1	400	85	30	TO-247 TO-3P
UFR14040C	UltraFast	140	400	420	1.5	70	1	400	80	30	TO-247 TO-3P
UHR1540	HyperFast	15	400	180	1.5	15	100	400	89(Typ)	15	TO-220 TO-220F
UHR1040C	HyperFast	10	400	40	1.5	10	10	400	30(Typ)	1	TO-220
RS1G	Fast	1	400	30	1.3	1	5	400	150	0.5	SMA DO-41
IN5406G	Glass-passivated	3	600	200	1.2	3	5	600	-	-	DO-201AD

DIODE List > Small Signal Switching Diode

PartNo. (勾選方式)	Description	VRRM (V) (Range)	IF(AV) (mA) (Range)	IR MAX.(uA)	@V _R (V)	VF MAX.(V) (Range)	@IF (mA)	t _{rr} (ns) (Range)	CT@0V (pF)	PowerDissipation PTOT(mW)
MMBD6100	Small Signal Switching Diode	70	200	0.1	50	1.1	100	4	2.5	350
BAW56	Small Signal Switching Diode	75	150	2.5	75	1.25	150	4	2	350
BAW56W	Small Signal Switching Diode	75	150	2.5	75	1.25	150	4	2	200
BAV70W	Small Signal Switching Diode	75	150	2.5	75	1.25	150	4	2	200
BAV70S	Small Signal Switching Diode	75	150	0.5	80	1.25	150	4	-	350
BAV70T	Small Signal Switching Diode	75	150	2	75	1.25	150	4	-	150
MMBD7000	Small Signal Switching Diode	75	300	3	100	1.25	150	4	2	350
UMR11N	Small Signal Switching Diode	80	100	0.1	70	1.2	100	4	3.5	200
BAV70	Small Signal Switching Diode	85	150	2.5	85	1.25	150	4	2	350
BAV99	Small Signal Switching Diode	85	200	2.5	85	1.25	150	6	1.5	350/200/150
BAV99	Small Signal Switching Diode	85	200	2.5	85	1.25	150	6	1.5	200
ISS184	Small Signal Switching Diode	85	300	0.5	80	1.2	100		3	
ISS355	Small Signal Switching Diode	90	100	0.1	80	1.2	100	4	3	-
ISS400	Small Signal Switching Diode	90	100	0.1	80	1.2	100	4	-	150
ISS133	Small Signal Switching Diode	90	130	0.5	80	1.2	100	4		300
IN4148	Small Signal Switching Diode	100	200	5	75	1	10	4	4	400\200\270\350
MMBD4148	Small Signal Switching Diode	100	250	5	75	0.855	10	4	4	220
MMBD4148T	Small Signal Switching Diode	100	200	5	75	0.855	10	4	4	200
MMBD4148CA	Small Signal Switching Diode	100	200	5	75	0.855	10	4	4	350
MMBD4148CC	Small Signal Switching Diode	100	200	5	75	0.855	10	4	4	350
MMBD4148SE	Small Signal Switching Diode	100	200	5	75	0.855	10	4	4	350
BAS299	Small Signal Switching Diode	100	250	1	100	1.25	300	6	3	250
BAV20W	Small Signal Switching Diode	200	200	0.1	150	1.25	200	50	1.5	410
BAS21	Small Signal Switching Diode	250	200	0.1	200	1.25	200	50	5	250/410
BAV199	Low Leakage Switching Diode	85	160	0.05	75	1.25	150	3000	2	250

BAV199W	Low Leakage Switching Diode	85	160	0.005	75	1.25	150	3000	2	250
---------	--------------------------------	----	-----	-------	----	------	-----	------	---	-----

Package (勾选方式)
SOT-23
SOT-23
SOT-323
SOT-323
SOT-363
SOT-523
SOT-23
SOT-363
SOT-23
SOT-23 SOT-323 SOT-523
SOT-363
SOT-23
SOD-323
SOD-523
DO-34
SOD-123 SOD-323 SOD-523 SOT-23 SOT-323 SOD-80 SOT-23 SOT-323 SOT-523 SOD-123
SOT-523
SOT-23
SOT-23
SOT-23
SOT-23
SOD-123 SOD-323
SOT-23-3(AE2) SOD-123 SOT-23(SC-59) SOD-323
SOT-23

SOT-323

DIODE List > Bridge Diode

PartNo. (勾选方式)	I _o (A) (Range)	VRM (V) (Range)	I _{FSM} (A)	VFMdiode MAX.(V) (Range)	VFMdiode Conditions IF(A)	IRM(IR) Rating MAX.(μA)	IRM(IR) Conditions VR(V)
DB106G	1	800	50	1.1	1	10	800
DB107G	1	1000	50	1.1	1	10	1000
SBS34	3	40	80	0.55	3	500	40
MB05FU	1	50	35	1.1	1	5	50
MB1FU	1	100	35	1.1	1	5	100
MB2FU	1	200	35	1.1	1	5	200
MB4FU	1	400	35	1.1	1	5	400
MB6FU	1	600	35	1.1	1	5	600
MB8FU	1	800	35	1.1	1	5	800
MB10FU	1	1000	35	1.1	1	5	1000
MB05S	0.8	50	30	1.1	0.8	5	50
MB1S	0.8	100	30	1.1	0.8	5	100
MB2S	0.8	200	30	1.1	0.8	5	200
MB4S	0.8	400	30	1.1	0.8	5	400
MB6S	0.8	600	30	1.1	0.8	5	600
MB8S	0.8	800	30	1.1	0.8	5	800
MB10S	0.8	1000	30	1.1	0.8	5	1000
MB1SU	1	100	35	1.1	1	5	100
MB2SU	1	200	35	1.1	1	5	200
MB4SU	1	400	35	1.1	1	5	400
MB6SU	1	600	35	1.1	1	5	600
MB8SU	1	800	35	1.1	1	5	800
MB10SU	1	1000	35	1.1	1	5	1000
ABS2	0.8	200	30	0.95	0.4	5	200
ABS4	0.8	400	30	0.95	0.4	5	400
ABS6	0.8	600	30	0.95	0.4	5	600
ABS8	0.8	800	30	0.95	0.4	5	800
ABS10	0.8	1000	30	0.95	0.4	5	1000
ABS2U	1	200	35	1.1	1	5	200
ABS4U	1	400	35	1.1	1	5	400
ABS6U	1	600	35	1.1	1	5	600
ABS8U	1	800	35	1.1	1	5	800
ABS10U	1	1000	35	1.1	1	5	1000
ABS22	2	200	60	0.95	1	5	200
ABS24	2	400	60	0.95	1	5	400
ABS26	2	600	60	0.95	1	5	600
ABS28	2	800	60	0.95	1	5	800
ABS210	2	1000	60	0.95	1	5	1000
GBJ5006	5.2	600	450	1	25	5	600
GBJ1506	15	600	240	1	7.5	5	600
UYBS3010	3	1000	110	1	1.5	5	1000

DIODE List > ZenerDiode

PartNo. (勾通方式)	Power Dissipation Pd (mW)	ZenerVoltage eRange VZ@IZT Nom.V (Range)	ZenerVoltage eRange VZ@IZT Min.V (Range)	ZenerVoltage eRange VZ@IZT Max.V (Range)	ZenerImpedance MAXZZT@IZT Ω	ZenerImpedance MAXZZT@IZT mA	Reverse LeakageCurrent MAXIR@VR (uA)	Reverse LeakageCurrent MAXIR@VR (V)	Package (勾通方式)
BZT52B2V4S	200	2.4	2.352	2.448	85	5	100	1	SOD-123
BZT52B2V7S	200	2.7	2.64	2.754	83	5	75	1	SOD-123
BZT52B3S	200	3	2.94	3.06	95	5	50	1	SOD-123
BZT52B3V3S	200	3.3	3.234	3.366	95	5	25	1	SOD-123
BZT52B3V6S	200	3.6	3.52	3.672	95	5	15	1	SOD-123
BZT52B3V9S	200	3.9	3.822	3.978	95	5	10	1	SOD-123
BZT52B4V3S	200	4.3	4.214	4.386	95	5	5	1	SOD-123
BZT52B4V7S	200	4.7	4.606	4.794	78	5	5	1	SOD-123
BZT52B5V1S	200	5.1	4.998	5.202	60	5	0.1	0.8	SOD-123
BZT52B5V6S	200	5.6	5.488	5.712	40	5	0.1	1	SOD-123
BZT52B6V2S	200	6.2	6.076	6.324	10	5	0.1	2	SOD-123
BZT52B6V8S	200	6.8	6.664	6.936	8	5	0.1	3	SOD-123
BZT52B7V5S	200	7.5	7.35	7.65	7	5	0.1	5	SOD-123
BZT52B8V2S	200	8.2	8.036	8.364	7	5	0.1	6	SOD-123
BZT52B8V7S	200	8.7	8.526	8.874	7	5	0.1	6.5	SOD-123
BZT52B9V1S	200	9.1	8.918	9.282	10	5	0.1	7	SOD-123
BZT52B10S	200	10	9.8	10.2	15	5	0.1	7.5	SOD-123
BZT52B11S	200	11	10.78	11.22	20	5	0.1	8.5	SOD-123
BZT52B12S	200	12	11.76	12.24	20	5	0.1	9	SOD-123
BZT52B13S	200	13	12.74	13.26	25	5	0.1	10	SOD-123
BZT52B14S	200	14	13.72	14.28	25	5	0.1	10.5	SOD-123
BZT52B15S	200	15	14.7	15.3	30	5	0.1	11	SOD-123
BZT52B16S	200	16	15.68	16.32	40	5	0.1	12	SOD-123
BZT52B17S	200	17	16.66	17.34	40	5	0.1	13	SOD-123
BZT52B18S	200	18	17.64	18.36	50	5	0.1	14	SOD-123
BZT52B20S	200	20	19.6	20.4	50	5	0.1	15	SOD-123
BZT52B22S	200	22	21.56	22.44	55	5	0.1	17	SOD-123
BZT52B24S	200	24	23.52	24.48	80	5	0.1	18	SOD-123
BZT52B27S	200	27	26.46	27.54	80	5	0.1	20	SOD-123
BZT52B28S	200	28	27.44	28.56	80	5	0.1	22	SOD-123
BZT52B30S	200	30	29.4	30.6	80	5	0.1	22.5	SOD-123
BZT52B33S	200	33	32.34	33.66	80	5	0.1	25	SOD-123
BZT52B36S	200	36	35.28	36.72	90	5	0.1	27	SOD-123
BZT52B39S	200	39	38.22	39.78	90	5	0.1	29	SOD-123
BZT52B43S	200	43	42.14	43.86	100	5	0.1	32	SOD-123
BZT52B47S	200	47	46.06	47.94	100	5	0.1	35	SOD-123
BZT52B51S	200	51	49.98	52.02	100	5	0.1	38	SOD-123
BZT52B56S	200	56	54.88	57.12	135	2.5	0.1	42	SOD-123
BZT52B62S	200	62	60.76	63.24	150	2.5	0.1	46	SOD-123
BZT52B68S	200	68	66.64	69.36	200	2.5	0.1	51	SOD-123
BZT52B75S	200	75	73.5	76.5	250	2.5	0.1	56	SOD-123
BZT52B2V4S	200	2.4	2.352	2.448	85	5	100	1	SOD-323
BZT52B2V7S	200	2.7	2.64	2.754	83	5	75	1	SOD-323
BZT52B3S	200	3	2.94	3.06	95	5	50	1	SOD-323
BZT52B3V3S	200	3.3	3.234	3.366	95	5	25	1	SOD-323

DIODE List > ZenerDiode

BZT52B3V6S	200	3.6	3.52	3.672	95	5	15	1	SOD-323
BZT52B3V9S	200	3.9	3.822	3.978	95	5	10	1	SOD-323
BZT52B4V3S	200	4.3	4.214	4.386	95	5	5	1	SOD-323
BZT52B4V7S	200	4.7	4.606	4.794	78	5	5	1	SOD-323
BZT52B5V1S	200	5.1	4.998	5.202	60	5	0.1	0.8	SOD-323
BZT52B5V6S	200	5.6	5.488	5.712	40	5	0.1	1	SOD-323
BZT52B6V2S	200	6.2	6.076	6.324	10	5	0.1	2	SOD-323
BZT52B6V8S	200	6.8	6.664	6.936	8	5	0.1	3	SOD-323
BZT52B7V5S	200	7.5	7.35	7.65	7	5	0.1	5	SOD-323
BZT52B8V2S	200	8.2	8.036	8.364	7	5	0.1	6	SOD-323
BZT52B8V7S	200	8.7	8.526	8.874	7	5	0.1	6.5	SOD-323
BZT52B9V1S	200	9.1	8.918	9.282	10	5	0.1	7	SOD-323
BZT52B10S	200	10	9.8	10.2	15	5	0.1	7.5	SOD-323
BZT52B11S	200	11	10.78	11.22	20	5	0.1	8.5	SOD-323
BZT52B12S	200	12	11.76	12.24	20	5	0.1	9	SOD-323
BZT52B13S	200	13	12.74	13.26	25	5	0.1	10	SOD-323
BZT52B14S	200	14	13.72	14.28	25	5	0.1	10.5	SOD-323
BZT52B15S	200	15	14.7	15.3	30	5	0.1	11	SOD-323
BZT52B16S	200	16	15.68	16.32	40	5	0.1	12	SOD-323
BZT52B17S	200	17	16.66	17.34	40	5	0.1	13	SOD-323
BZT52B18S	200	18	17.64	18.36	50	5	0.1	14	SOD-323
BZT52B20S	200	20	19.6	20.4	50	5	0.1	15	SOD-323
BZT52B22S	200	22	21.56	22.44	55	5	0.1	17	SOD-323
BZT52B24S	200	24	23.52	24.48	80	5	0.1	18	SOD-323
BZT52B27S	200	27	26.46	27.54	80	5	0.1	20	SOD-323
BZT52B28S	200	28	27.44	28.56	80	5	0.1	22	SOD-323
BZT52B30S	200	30	29.4	30.6	80	5	0.1	22.5	SOD-323
BZT52B33S	200	33	32.34	33.66	80	5	0.1	25	SOD-323
BZT52B36S	200	36	35.28	36.72	90	5	0.1	27	SOD-323
BZT52B39S	200	39	38.22	39.78	90	5	0.1	29	SOD-323
BZT52B43S	200	43	42.14	43.86	100	5	0.1	32	SOD-323
BZT52B47S	200	47	46.06	47.94	100	5	0.1	35	SOD-323
BZT52B51S	200	51	49.98	52.02	100	5	0.1	38	SOD-323
BZT52B56S	200	56	54.88	57.12	135	2.5	0.1	42	SOD-323
BZT52B62S	200	62	60.76	63.24	150	2.5	0.1	46	SOD-323
BZT52B68S	200	68	66.64	69.36	200	2.5	0.1	51	SOD-323
BZT52B75S	200	75	73.5	76.5	250	2.5	0.1	56	SOD-323
BZT52B2V4S	200	2.4	2.352	2.448	85	5	100	1	SOT-23
BZT52B2V7S	200	2.7	2.64	2.754	83	5	75	1	SOT-23
BZT52B3S	200	3	2.94	3.06	95	5	50	1	SOT-23
BZT52B3V3S	200	3.3	3.234	3.366	95	5	25	1	SOT-23
BZT52B3V6S	200	3.6	3.52	3.672	95	5	15	1	SOT-23
BZT52B3V9S	200	3.9	3.822	3.978	95	5	10	1	SOT-23
BZT52B4V3S	200	4.3	4.214	4.386	95	5	5	1	SOT-23
BZT52B4V7S	200	4.7	4.606	4.794	78	5	5	1	SOT-23
BZT52B5V1S	200	5.1	4.998	5.202	60	5	0.1	0.8	SOT-23
BZT52B5V6S	200	5.6	5.488	5.712	40	5	0.1	1	SOT-23
BZT52B6V2S	200	6.2	6.076	6.324	10	5	0.1	2	SOT-23

DIODE List > ZenerDiode

BZT52B6V8S	200	6.8	6.664	6.936	8	5	0.1	3	SOT-23
BZT52B7V5S	200	7.5	7.35	7.65	7	5	0.1	5	SOT-23
BZT52B8V2S	200	8.2	8.036	8.364	7	5	0.1	6	SOT-23
BZT52B8V7S	200	8.7	8.526	8.874	7	5	0.1	6.5	SOT-23
BZT52B9V1S	200	9.1	8.918	9.282	10	5	0.1	7	SOT-23
BZT52B10S	200	10	9.8	10.2	15	5	0.1	7.5	SOT-23
BZT52B11S	200	11	10.78	11.22	20	5	0.1	8.5	SOT-23
BZT52B12S	200	12	11.76	12.24	20	5	0.1	9	SOT-23
BZT52B13S	200	13	12.74	13.26	25	5	0.1	10	SOT-23
BZT52B14S	200	14	13.72	14.28	25	5	0.1	10.5	SOT-23
BZT52B15S	200	15	14.7	15.3	30	5	0.1	11	SOT-23
BZT52B16S	200	16	15.68	16.32	40	5	0.1	12	SOT-23
BZT52B17S	200	17	16.66	17.34	40	5	0.1	13	SOT-23
BZT52B18S	200	18	17.64	18.36	50	5	0.1	14	SOT-23
BZT52B20S	200	20	19.6	20.4	50	5	0.1	15	SOT-23
BZT52B22S	200	22	21.56	22.44	55	5	0.1	17	SOT-23
BZT52B24S	200	24	23.52	24.48	80	5	0.1	18	SOT-23
BZT52B27S	200	27	26.46	27.54	80	5	0.1	20	SOT-23
BZT52B28S	200	28	27.44	28.56	80	5	0.1	22	SOT-23
BZT52B30S	200	30	29.4	30.6	80	5	0.1	22.5	SOT-23
BZT52B33S	200	33	32.34	33.66	80	5	0.1	25	SOT-23
BZT52B36S	200	36	35.28	36.72	90	5	0.1	27	SOT-23
BZT52B39S	200	39	38.22	39.78	90	5	0.1	29	SOT-23
BZT52B43S	200	43	42.14	43.86	100	5	0.1	32	SOT-23
BZT52B47S	200	47	46.06	47.94	100	5	0.1	35	SOT-23
BZT52B51S	200	51	49.98	52.02	100	5	0.1	38	SOT-23
BZT52B56S	200	56	54.88	57.12	135	2.5	0.1	42	SOT-23
BZT52B62S	200	62	60.76	63.24	150	2.5	0.1	46	SOT-23
BZT52B68S	200	68	66.64	69.36	200	2.5	0.1	51	SOT-23
BZT52B75S	200	75	73.5	76.5	250	2.5	0.1	56	SOT-23
UMMSZ5221B	500	2.4	2.28	2.52	30	20	100	1	LL-34
UMMSZ5222B	500	2.5	2.38	2.63	30	20	100	1	LL-34
UMMSZ5223B	500	2.7	2.57	2.84	30	20	75	1	LL-34
UMMSZ5224B	500	2.8	2.66	2.94	30	20	75	1	LL-34
UMMSZ5225B	500	3	2.85	3.15	30	20	50	1	LL-34
UMMSZ5226B	500	3.3	3.14	3.47	28	20	25	1	LL-34
UMMSZ5227B	500	3.6	3.42	3.78	24	20	15	1	LL-34
UMMSZ5228B	500	3.9	3.71	4.1	23	20	10	1	LL-34
UMMSZ5230B	500	4.7	4.47	4.94	19	20	5	2	LL-34
UMMSZ5231B	500	5.1	4.85	5.36	17	20	5	2	LL-34
UMMSZ5232B	500	5.6	5.32	5.88	11	20	5	3	LL-34
UMMSZ5233B	500	6	5.7	6.3	7	20	5	3.5	LL-34
UMMSZ5234B	500	6.2	5.89	6.51	7	20	5	4	LL-34
UMMSZ5235B	500	6.8	6.46	7.14	5	20	3	5	LL-34
UMMSZ5236B	500	7.5	7.13	7.88	6	20	3	6	LL-34
UMMSZ5237B	500	8.2	7.79	8.61	8	20	3	6	LL-34
UMMSZ5238B	500	8.7	8.27	9.14	8	20	3	6.5	LL-34
UMMSZ5239B	500	9.1	8.65	9.56	10	20	3	6.5	LL-34

DIODE List > ZenerDiode

UMMSZ5240B	500	10	9.5	10.5	17	20	3	8	LL-34
UMMSZ5241B	500	11	10.45	11.55	22	20	2	8.4	LL-34
UMMSZ5242B	500	12	11.4	12.6	30	20	1	9.1	LL-34
UMMSZ5243B	500	13	12.35	13.65	13	9.5	1	9.9	LL-34
UMMSZ5244B	500	14	13.3	14.7	15	9	0.1	10.5	LL-34
UMMSZ5245B	500	15	14.25	15.75	16	8.5	0.1	11	LL-34
UMMSZ5246B	500	16	15.2	16.8	17	7.8	0.1	12	LL-34
UMMSZ5247B	500	17	16.15	17.85	19	7.5	0.1	13	LL-34
UMMSZ5248B	500	18	17.1	18.9	21	7	0.1	14	LL-34
UMMSZ5249B	500	19	18.05	19.95	23	6.6	0.1	14	LL-34
UMMSZ5250B	500	20	19	21	25	6.2	0.1	15	LL-34
UMMSZ5251B	500	22	20.9	23.1	29	5.6	0.1	17	LL-34
UMMSZ5252B	500	24	22.8	25.2	33	5.2	0.1	18	LL-34
UMMSZ5253B	500	25	23.75	26.25	35	5	0.1	19	LL-34
UMMSZ5254B	500	27	25.65	28.35	41	5	0.1	21	LL-34
UMMSZ5255B	500	28	26.6	29.4	44	4.5	0.1	21	LL-34
UMMSZ5256B	500	30	28.5	31.5	49	4.2	0.1	23	LL-34
UMMSZ5257B	500	33	31.35	34.65	58	3.8	0.1	25	LL-34
UMMSZ5258B	500	36	34.2	37.8	70	3.4	0.1	27	LL-34
UMMSZ5259B	500	39	37.05	40.95	80	3.2	0.1	30	LL-34
UMMSZ5231A	500	5.1	5	5.2	17	20	5	2	SOD-123
UMMSZ5234A	500	6.2	6.08	6.32	7	20	5	4	SOD-123
UMMSZ5248A	500	18	17.64	18.36	21	7	0.1	14	SOD-123
UMMSZ5250A	500	20	19.6	20.4	25	6.2	0.1	15	SOD-123
UMMSZ5221B	500	2.4	2.28	2.52	30	20	100	1	SOD-123
UMMSZ5222B	500	2.5	2.38	2.63	30	20	100	1	SOD-123
UMMSZ5223B	500	2.7	2.57	2.84	30	20	75	1	SOD-123
UMMSZ5224B	500	2.8	2.66	2.94	30	20	75	1	SOD-123
UMMSZ5225B	500	3	2.85	3.15	30	20	50	1	SOD-123
UMMSZ5226B	500	3.3	3.14	3.47	28	20	25	1	SOD-123
UMMSZ5227B	500	3.6	3.42	3.78	24	20	15	1	SOD-123
UMMSZ5228B	500	3.9	3.71	4.1	23	20	10	1	SOD-123
UMMSZ5229B	500	4.3	4.09	4.52	22	20	5	1	SOD-123
UMMSZ5230B	500	4.7	4.47	4.94	19	20	5	2	SOD-123
UMMSZ5231B	500	5.1	4.85	5.36	17	20	5	2	SOD-123
UMMSZ5232B	500	5.6	5.32	5.88	11	20	5	3	SOD-123
UMMSZ5233B	500	6	5.7	6.3	7	20	5	3.5	SOD-123
UMMSZ5234B	500	6.2	5.89	6.51	7	20	5	4	SOD-123
UMMSZ5235B	500	6.8	6.46	7.14	5	20	3	5	SOD-123
UMMSZ5236B	500	7.5	7.13	7.88	6	20	3	6	SOD-123
UMMSZ5237B	500	8.2	7.79	8.61	8	20	3	6	SOD-123
UMMSZ5238B	500	8.7	8.27	9.14	8	20	3	6.5	SOD-123
UMMSZ5239B	500	9.1	8.65	9.56	10	20	3	6.5	SOD-123
UMMSZ5240B	500	10	9.5	10.5	17	20	3	8	SOD-123
UMMSZ5241B	500	11	10.45	11.55	22	20	2	8.4	SOD-123
UMMSZ5242B	500	12	11.4	12.6	30	20	1	9.1	SOD-123
UMMSZ5243B	500	13	12.35	13.65	13	9.5	1	9.9	SOD-123
UMMSZ5244B	500	14	13.3	14.7	15	9	0.1	10.5	SOD-123

DIODE List > ZenerDiode

UMMSZ5245B	500	15	14.25	15.75	16	8.5	0.1	11	SOD-123
UMMSZ5246B	500	16	15.2	16.8	17	7.8	0.1	12	SOD-123
UMMSZ5247B	500	17	16.15	17.85	19	7.5	0.1	13	SOD-123
UMMSZ5248B	500	18	17.1	18.9	21	7	0.1	14	SOD-123
UMMSZ5249B	500	19	18.05	19.95	23	6.6	0.1	14	SOD-123
UMMSZ5250B	500	20	19	21	25	6.2	0.1	15	SOD-123
UMMSZ5251B	500	22	20.9	23.1	29	5.6	0.1	17	SOD-123
UMMSZ5252B	500	24	22.8	25.2	33	5.2	0.1	18	SOD-123
UMMSZ5253B	500	25	23.75	26.25	35	5	0.1	19	SOD-123
UMMSZ5254B	500	27	25.65	28.35	41	5	0.1	21	SOD-123
UMMSZ5255B	500	28	26.6	29.4	44	4.5	0.1	21	SOD-123
UMMSZ5256B	500	30	28.5	31.5	49	4.2	0.1	23	SOD-123
UMMSZ5257B	500	33	31.35	34.65	58	3.8	0.1	25	SOD-123
UMMSZ5258B	500	36	34.2	37.8	70	3.4	0.1	27	SOD-123
UMMSZ5259B	500	39	37.05	40.95	80	3.2	0.1	30	SOD-123
UMMSZ5260B	500	43	40.85	45.15	93	3	0.1	33	SOD-123
UMMSZ5261B	500	47	44.65	49.35	105	2.7	0.1	36	SOD-123
UMMSZ5262B	500	51	48.45	53.55	125	2.5	0.1	39	SOD-123
UMMSZ5221B	330	2.4	2.28	2.52	30	20	100	1	SOD-323
UMMSZ5222B	330	2.5	2.38	2.63	30	20	100	1	SOD-323
UMMSZ5223B	330	2.7	2.57	2.84	30	20	75	1	SOD-323
UMMSZ5224B	330	2.8	2.66	2.94	30	20	75	1	SOD-323
UMMSZ5225B	330	3	2.85	3.15	30	20	50	1	SOD-323
UMMSZ5226B	330	3.3	3.14	3.47	28	20	25	1	SOD-323
UMMSZ5227B	330	3.6	3.42	3.78	24	20	15	1	SOD-323
UMMSZ5228B	330	3.9	3.71	4.1	23	20	10	1	SOD-323
UMMSZ5229B	330	4.3	4.09	4.52	22	20	5	1	SOD-323
UMMSZ5230B	330	4.7	4.47	4.94	19	20	5	2	SOD-323
UMMSZ5231B	330	5.1	4.85	5.36	17	20	5	2	SOD-323
UMMSZ5232B	330	5.6	5.32	5.88	11	20	5	3	SOD-323
UMMSZ5233B	330	6	5.7	6.3	7	20	5	3.5	SOD-323
UMMSZ5234B	330	6.2	5.89	6.51	7	20	5	4	SOD-323
UMMSZ5235B	330	6.8	6.46	7.14	5	20	3	5	SOD-323
UMMSZ5236B	330	7.5	7.13	7.88	6	20	3	6	SOD-323
UMMSZ5237B	330	8.2	7.79	8.61	8	20	3	6	SOD-323
UMMSZ5238B	330	8.7	8.27	9.14	8	20	3	6.5	SOD-323
UMMSZ5239B	330	9.1	8.65	9.56	10	20	3	6.5	SOD-323
UMMSZ5240B	330	10	9.5	10.5	17	20	3	8	SOD-323
UMMSZ5241B	330	11	10.45	11.55	22	20	2	8.4	SOD-323
UMMSZ5242B	330	12	11.4	12.6	30	20	1	9.1	SOD-323
UMMSZ5243B	330	13	12.35	13.65	13	9.5	1	9.9	SOD-323
UMMSZ5244B	330	14	13.3	14.7	15	9	0.1	10.5	SOD-323
UMMSZ5245B	330	15	14.25	15.75	16	8.5	0.1	11	SOD-323
UMMSZ5246B	330	16	15.2	16.8	17	7.8	0.1	12	SOD-323
UMMSZ5247B	330	17	16.15	17.85	19	7.5	0.1	13	SOD-323
UMMSZ5248B	330	18	17.1	18.9	21	7	0.1	14	SOD-323
UMMSZ5249B	330	19	18.05	19.95	23	6.6	0.1	14	SOD-323
UMMSZ5250B	330	20	19	21	25	6.2	0.1	15	SOD-323

DIODE List > ZenerDiode

UMMSZ5251B	330	22	20.9	23.1	29	5.6	0.1	17	SOD-323
UMMSZ5252B	330	24	22.8	25.2	33	5.2	0.1	18	SOD-323
UMMSZ5253B	330	25	23.75	26.25	35	5	0.1	19	SOD-323
UMMSZ5254B	330	27	25.65	28.35	41	5	0.1	21	SOD-323
UMMSZ5255B	330	28	26.6	29.4	44	4.5	0.1	21	SOD-323
UMMSZ5256B	330	30	28.5	31.5	49	4.2	0.1	23	SOD-323
UMMSZ5257B	330	33	31.35	34.65	58	3.8	0.1	25	SOD-323
UMMSZ5258B	330	36	34.2	37.8	70	3.4	0.1	27	SOD-323
UMMSZ5259B	330	39	37.05	40.95	80	3.2	0.1	30	SOD-323
UMMSZ5260B	330	43	40.85	45.15	93	3	0.1	33	SOD-323
UMMSZ5261B	330	47	44.65	49.35	105	2.7	0.1	36	SOD-323
UMMSZ5262B	330	51	48.45	53.55	125	2.5	0.1	39	SOD-323
UMMSZ5221B	250	2.4	2.28	2.52	30	20	100	1	SOD-523
UMMSZ5222B	250	2.5	2.38	2.63	30	20	100	1	SOD-523
UMMSZ5223B	250	2.7	2.57	2.84	30	20	75	1	SOD-523
UMMSZ5224B	250	2.8	2.66	2.94	30	20	75	1	SOD-523
UMMSZ5225B	250	3	2.85	3.15	30	20	50	1	SOD-523
UMMSZ5226B	250	3.3	3.14	3.47	28	20	25	1	SOD-523
UMMSZ5227B	250	3.6	3.42	3.78	24	20	15	1	SOD-523
UMMSZ5228B	250	3.9	3.71	4.1	23	20	10	1	SOD-523
UMMSZ5229B	250	4.3	4.09	4.52	22	20	5	1	SOD-523
UMMSZ5230B	250	4.7	4.47	4.94	19	20	5	2	SOD-523
UMMSZ5231B	250	5.1	4.85	5.36	17	20	5	2	SOD-523
UMMSZ5232B	250	5.6	5.32	5.88	11	20	5	3	SOD-523
UMMSZ5233B	250	6	5.7	6.3	7	20	5	3.5	SOD-523
UMMSZ5234B	250	6.2	5.89	6.51	7	20	5	4	SOD-523
UMMSZ5235B	250	6.8	6.46	7.14	5	20	3	5	SOD-523
UMMSZ5236B	250	7.5	7.13	7.88	6	20	3	6	SOD-523
UMMSZ5237B	250	8.2	7.79	8.61	8	20	3	6	SOD-523
UMMSZ5238B	250	8.7	8.27	9.14	8	20	3	6.5	SOD-523
UMMSZ5239B	250	9.1	8.65	9.56	10	20	3	6.5	SOD-523
UMMSZ5240B	250	10	9.5	10.5	17	20	3	8	SOD-523
UMMSZ5241B	250	11	10.45	11.55	22	20	2	8.4	SOD-523
UMMSZ5242B	250	12	11.4	12.6	30	20	1	9.1	SOD-523
UMMSZ5243B	250	13	12.35	13.65	13	9.5	1	9.9	SOD-523
UMMSZ5244B	250	14	13.3	14.7	15	9	0.1	10.5	SOD-523
UMMSZ5245B	250	15	14.25	15.75	16	8.5	0.1	11	SOD-523
UMMSZ5246B	250	16	15.2	16.8	17	7.8	0.1	12	SOD-523
UMMSZ5247B	250	17	16.15	17.85	19	7.5	0.1	13	SOD-523
UMMSZ5248B	250	18	17.1	18.9	21	7	0.1	14	SOD-523
UMMSZ5249B	250	19	18.05	19.95	23	6.6	0.1	14	SOD-523
UMMSZ5250B	250	20	19	21	25	6.2	0.1	15	SOD-523
UMMSZ5251B	250	22	20.9	23.1	29	5.6	0.1	17	SOD-523
UMMSZ5252B	250	24	22.8	25.2	33	5.2	0.1	18	SOD-523
UMMSZ5253B	250	25	23.75	26.25	35	5	0.1	19	SOD-523
UMMSZ5254B	250	27	25.65	28.35	41	5	0.1	21	SOD-523
UMMSZ5255B	250	28	26.6	29.4	44	4.5	0.1	21	SOD-523
UMMSZ5256B	250	30	28.5	31.5	49	4.2	0.1	23	SOD-523

DIODE List > ZenerDiode

UMMSZ5257B	250	33	31.35	34.65	58	3.8	0.1	25	SOD-523
UMMSZ5258B	250	36	34.2	37.8	70	3.4	0.1	27	SOD-523
UMMSZ5259B	250	39	37.05	40.95	80	3.2	0.1	30	SOD-523
UMMSZ5260B	250	43	40.85	45.15	93	3	0.1	33	SOD-523
UMMSZ5261B	250	47	44.65	49.35	105	2.7	0.1	36	SOD-523
UMMSZ5262B	250	51	48.45	53.55	125	2.5	0.1	39	SOD-523
UMMSZ5221B	200	2.4	2.28	2.52	30	20	100	1	SOT-23
UMMSZ5222B	200	2.5	2.38	2.63	30	20	100	1	SOT-23
UMMSZ5223B	200	2.7	2.57	2.84	30	20	75	1	SOT-23
UMMSZ5224B	200	2.8	2.66	2.94	30	20	75	1	SOT-23
UMMSZ5225B	200	3	2.85	3.15	30	20	50	1	SOT-23
UMMSZ5226B	200	3.3	3.14	3.47	28	20	25	1	SOT-23
UMMSZ5227B	200	3.6	3.42	3.78	24	20	15	1	SOT-23
UMMSZ5228B	200	3.9	3.71	4.1	23	20	10	1	SOT-23
UMMSZ5229B	200	4.3	4.09	4.52	22	20	5	1	SOT-23
UMMSZ5230B	200	4.7	4.47	4.94	19	20	5	2	SOT-23
UMMSZ5231B	200	5.1	4.85	5.36	17	20	5	2	SOT-23
UMMSZ5232B	200	5.6	5.32	5.88	11	20	5	3	SOT-23
UMMSZ5233B	200	6	5.7	6.3	7	20	5	3.5	SOT-23
UMMSZ5234B	200	6.2	5.89	6.51	7	20	5	4	SOT-23
UMMSZ5235B	200	6.8	6.46	7.14	5	20	3	5	SOT-23
UMMSZ5236B	200	7.5	7.13	7.88	6	20	3	6	SOT-23
UMMSZ5237B	200	8.2	7.79	8.61	8	20	3	6	SOT-23
UMMSZ5238B	200	8.7	8.27	9.14	8	20	3	6.5	SOT-23
UMMSZ5239B	200	9.1	8.65	9.56	10	20	3	6.5	SOT-23
UMMSZ5240B	200	10	9.5	10.5	17	20	3	8	SOT-23
UMMSZ5241B	200	11	10.45	11.55	22	20	2	8.4	SOT-23
UMMSZ5242B	200	12	11.4	12.6	30	20	1	9.1	SOT-23
UMMSZ5243B	200	13	12.35	13.65	13	9.5	1	9.9	SOT-23
UMMSZ5244B	200	14	13.3	14.7	15	9	0.1	10.5	SOT-23
UMMSZ5245B	200	15	14.25	15.75	16	8.5	0.1	11	SOT-23
UMMSZ5246B	200	16	15.2	16.8	17	7.8	0.1	12	SOT-23
UMMSZ5247B	200	17	16.15	17.85	19	7.5	0.1	13	SOT-23
UMMSZ5248B	200	18	17.1	18.9	21	7	0.1	14	SOT-23
UMMSZ5249B	200	19	18.05	19.95	23	6.6	0.1	14	SOT-23
UMMSZ5250B	200	20	19	21	25	6.2	0.1	15	SOT-23
UMMSZ5251B	200	22	20.9	23.1	29	5.6	0.1	17	SOT-23
UMMSZ5252B	200	24	22.8	25.2	33	5.2	0.1	18	SOT-23
UMMSZ5253B	200	25	23.75	26.25	35	5	0.1	19	SOT-23
UMMSZ5254B	200	27	25.65	28.35	41	5	0.1	21	SOT-23
UMMSZ5255B	200	28	26.6	29.4	44	4.5	0.1	21	SOT-23
UMMSZ5256B	200	30	28.5	31.5	49	4.2	0.1	23	SOT-23
UMMSZ5257B	200	33	31.35	34.65	58	3.8	0.1	25	SOT-23
UMMSZ5258B	200	36	34.2	37.8	70	3.4	0.1	27	SOT-23
UMMSZ5259B	200	39	37.05	40.95	80	3.2	0.1	30	SOT-23
UMMSZ5260B	200	43	40.85	45.15	93	3	0.1	33	SOT-23
UMMSZ5261B	200	47	44.65	49.35	105	2.7	0.1	36	SOT-23
UMMSZ5262B	200	51	48.45	53.55	125	2.5	0.1	39	SOT-23

DIODE List > ZenerDiode

ZD1.8	225	1.8	1.71	1.89	100	5	20	1	SOD-123
ZD2.4	225	2.4	2.28	2.52	100	5	20	1	SOD-123
ZD2.5	225	2.5	2.375	2.625	100	5	20	1	SOD-123
ZD3.3	225	3.3	3.135	3.465	100	5	10	1	SOD-123
ZD3.9	225	3.9	3.705	4.095	100	5	5	1	SOD-123
ZD4.3	225	4.3	4.085	4.515	100	5	5	1	SOD-123
ZD4.7	225	4.7	4.465	4.935	100	5	2	1	SOD-123
ZD5.1	225	5.1	4.845	5.355	80	5	2	1.5	SOD-123
ZD5.6	225	5.6	5.32	5.88	60	5	1	2.5	SOD-123
ZD6.0	225	6	5.7	6.3	60	5	1	2.5	SOD-123
ZD6.2	225	6.2	5.89	6.51	60	5	1	3	SOD-123
ZD6.8	225	6.8	6.46	7.14	40	5	0.5	3.5	SOD-123
ZD7.5	225	7.5	7.125	7.875	30	5	0.5	4	SOD-123
ZD8.2	225	8.2	7.79	8.61	30	5	0.5	5	SOD-123
ZD9.1	225	9.1	8.645	9.555	30	5	0.5	6	SOD-123
ZD10	225	10	9.5	10.5	30	5	0.1	7	SOD-123
ZD11	225	11	10.45	11.55	30	5	0.1	8	SOD-123
ZD12	225	12	11.4	12.6	30	5	0.1	9	SOD-123
ZD13	225	13	12.35	13.65	37	5	0.1	10	SOD-123
ZD15	225	15	14.25	15.75	42	5	0.1	11	SOD-123
ZD16	225	16	15.2	16.8	50	5	0.1	12	SOD-123
ZD18	225	18	17.1	18.9	65	5	0.1	13	SOD-123
ZD20	225	20	19	21	85	5	0.1	15	SOD-123
ZD22	225	22	20.9	23.1	100	5	0.1	17	SOD-123
ZD24	225	24	22.8	25.2	120	5	0.1	19	SOD-123
ZD25	225	25	23.75	26.25	130	5	0.1	19	SOD-123
ZD27	225	27	25.65	28.35	150	5	0.1	21	SOD-123
ZD30	225	30	28.5	31.5	200	5	0.1	23	SOD-123
ZD33	225	33	31.35	34.65	250	5	0.1	25	SOD-123
ZD36	225	36	34.2	37.8	300	5	0.1	27	SOD-123
ZD1.8	225	1.8	1.71	1.89	100	5	20	1	SOD-323
ZD2.4	225	2.4	2.28	2.52	100	5	20	1	SOD-323
ZD2.5	225	2.5	2.375	2.625	100	5	20	1	SOD-323
ZD3.3	225	3.3	3.135	3.465	100	5	10	1	SOD-323
ZD3.9	225	3.9	3.705	4.095	100	5	5	1	SOD-323
ZD4.3	225	4.3	4.085	4.515	100	5	5	1	SOD-323
ZD4.7	225	4.7	4.465	4.935	100	5	2	1	SOD-323
ZD5.1	225	5.1	4.845	5.355	80	5	2	1.5	SOD-323
ZD5.6	225	5.6	5.32	5.88	60	5	1	2.5	SOD-323
ZD6.0	225	6	5.7	6.3	60	5	1	2.5	SOD-323
ZD6.2	225	6.2	5.89	6.51	60	5	1	3	SOD-323
ZD6.8	225	6.8	6.46	7.14	40	5	0.5	3.5	SOD-323
ZD7.5	225	7.5	7.125	7.875	30	5	0.5	4	SOD-323
ZD8.2	225	8.2	7.79	8.61	30	5	0.5	5	SOD-323
ZD9.1	225	9.1	8.645	9.555	30	5	0.5	6	SOD-323
ZD10	225	10	9.5	10.5	30	5	0.1	7	SOD-323
ZD11	225	11	10.45	11.55	30	5	0.1	8	SOD-323
ZD12	225	12	11.4	12.6	30	5	0.1	9	SOD-323

DIODE List > ZenerDiode

ZD13	225	13	12.35	13.65	37	5	0.1	10	SOD-323
ZD15	225	15	14.25	15.75	42	5	0.1	11	SOD-323
ZD16	225	16	15.2	16.8	50	5	0.1	12	SOD-323
ZD18	225	18	17.1	18.9	65	5	0.1	13	SOD-323
ZD20	225	20	19	21	85	5	0.1	15	SOD-323
ZD22	225	22	20.9	23.1	100	5	0.1	17	SOD-323
ZD24	225	24	22.8	25.2	120	5	0.1	19	SOD-323
ZD25	225	25	23.75	26.25	130	5	0.1	19	SOD-323
ZD27	225	27	25.65	28.35	150	5	0.1	21	SOD-323
ZD30	225	30	28.5	31.5	200	5	0.1	23	SOD-323
ZD33	225	33	31.35	34.65	250	5	0.1	25	SOD-323
ZD36	225	36	34.2	37.8	300	5	0.1	27	SOD-323
ZD1.8	225	1.8	1.71	1.89	100	5	20	1	SOT-23
ZD2.4	225	2.4	2.28	2.52	100	5	20	1	SOT-23
ZD2.5	225	2.5	2.375	2.625	100	5	20	1	SOT-23
ZD3.3	225	3.3	3.135	3.465	100	5	10	1	SOT-23
ZD3.9	225	3.9	3.705	4.095	100	5	5	1	SOT-23
ZD4.3	225	4.3	4.085	4.515	100	5	5	1	SOT-23
ZD4.7	225	4.7	4.465	4.935	100	5	2	1	SOT-23
ZD5.1	225	5.1	4.845	5.355	80	5	2	1.5	SOT-23
ZD5.6	225	5.6	5.32	5.88	60	5	1	2.5	SOT-23
ZD6.0	225	6	5.7	6.3	60	5	1	2.5	SOT-23
ZD6.2	225	6.2	5.89	6.51	60	5	1	3	SOT-23
ZD6.8	225	6.8	6.46	7.14	40	5	0.5	3.5	SOT-23
ZD7.5	225	7.5	7.125	7.875	30	5	0.5	4	SOT-23
ZD8.2	225	8.2	7.79	8.61	30	5	0.5	5	SOT-23
ZD9.1	225	9.1	8.645	9.555	30	5	0.5	6	SOT-23
ZD10	225	10	9.5	10.5	30	5	0.1	7	SOT-23
ZD11	225	11	10.45	11.55	30	5	0.1	8	SOT-23
ZD12	225	12	11.4	12.6	30	5	0.1	9	SOT-23
ZD13	225	13	12.35	13.65	37	5	0.1	10	SOT-23
ZD15	225	15	14.25	15.75	42	5	0.1	11	SOT-23
ZD16	225	16	15.2	16.8	50	5	0.1	12	SOT-23
ZD18	225	18	17.1	18.9	65	5	0.1	13	SOT-23
ZD20	225	20	19	21	85	5	0.1	15	SOT-23
ZD22	225	22	20.9	23.1	100	5	0.1	17	SOT-23
ZD24	225	24	22.8	25.2	120	5	0.1	19	SOT-23
ZD25	225	25	23.75	26.25	130	5	0.1	19	SOT-23
ZD27	225	27	25.65	28.35	150	5	0.1	21	SOT-23
ZD30	225	30	28.5	31.5	200	5	0.1	23	SOT-23
ZD33	225	33	31.35	34.65	250	5	0.1	25	SOT-23
ZD36	225	36	34.2	37.8	300	5	0.1	27	SOT-23
1N4745A	1000	16	-	-	16	0.25	0.1	12.2	DO-41
UUDZ12B	200	12	11.74	12.24	30	5	0.1	9	SOD-323
BZT52C2V0S	200	2	1.91	2.09	100	5	150	1	SOD-123
BZT52C2V4S	200	2.4	2.2	2.6	100	5	50	1	SOD-123
BZT52C2V7S	200	2.7	2.5	2.9	100	5	20	1	SOD-123
BZT52C3S	200	3	2.8	3.2	100	5	10	1	SOD-123

DIODE List > ZenerDiode

BZT52C3V3S	200	3.3	3.1	3.5	95	5	5	1	SOD-123
BZT52C3V6S	200	3.6	3.4	3.8	95	5	5	1	SOD-123
BZT52C3V9S	200	3.9	3.7	4.1	90	5	3	1	SOD-123
BZT52C4V3S	200	4.3	4	4.6	90	5	3	1	SOD-123
BZT52C4V7S	200	4.7	4.4	5	90	5	2	2	SOD-123
BZT52C5V1S	200	5.1	4.8	5.4	60	5	1	2	SOD-123
BZT52C5V6S	200	5.6	5.2	6	40	5	3	2	SOD-123
BZT52C6V2S	200	6.2	5.8	6.6	10	5	2	4	SOD-123
BZT52C6V8S	200	6.8	6.4	7.2	15	5	1	4	SOD-123
BZT52C7V5S	200	7.5	7	7.9	15	5	0.7	5	SOD-123
BZT52C8V2S	200	8.2	7.7	8.7	15	5	0.2	5	SOD-123
BZT52C9V1S	200	9.1	8.5	9.6	15	5	0.2	6	SOD-123
BZT52C10S	200	10	9.4	10.6	15	5	0.1	7	SOD-123
BZT52C11S	200	11	10.4	11.6	15	5	0.1	8	SOD-123
BZT52C12S	200	12	11.4	12.7	25	5	0.1	8	SOD-123
BZT52C13S	200	13	12.4	14.1	30	5	0.1	8	SOD-123
BZT52C15S	200	15	13.8	15.6	30	5	0.1	10.5	SOD-123
BZT52C16S	200	16	15.3	17.1	40	5	0.1	11.2	SOD-123
BZT52C18S	200	18	16.8	19.1	45	5	0.1	12.6	SOD-123
BZT52C20S	200	20	18.8	21.2	55	5	0.1	14.4	SOD-123
BZT52C22S	200	22	20.8	23.3	55	5	0.1	16.4	SOD-123
BZT52C24S	200	24	22.8	25.6	70	5	0.1	18.4	SOD-123
BZT52C27S	200	27	25.1	28.9	80	2	0.1	21.4	SOD-123
BZT52C30S	200	30	28	32	80	2	0.1	24.4	SOD-123
BZT52C33S	200	33	31	35	80	2	0.1	27.4	SOD-123
BZT52C36S	200	36	34	38	90	2	0.1	30.4	SOD-123
BZT52C39S	200	39	37	41	130	2	0.1	33.4	SOD-123
BZT52C2V0S	200	2	1.91	2.09	100	5	150	1	SOD-323
BZT52C2V4S	200	2.4	2.2	2.6	100	5	50	1	SOD-323
BZT52C2V7S	200	2.7	2.5	2.9	100	5	20	1	SOD-323
BZT52C3S	200	3	2.8	3.2	100	5	10	1	SOD-323
BZT52C3V3S	200	3.3	3.1	3.5	95	5	5	1	SOD-323
BZT52C3V6S	200	3.6	3.4	3.8	95	5	5	1	SOD-323
BZT52C3V9S	200	3.9	3.7	4.1	90	5	3	1	SOD-323
BZT52C4V3S	200	4.3	4	4.6	90	5	3	1	SOD-323
BZT52C4V7S	200	4.7	4.4	5	90	5	2	2	SOD-323
BZT52C5V1S	200	5.1	4.8	5.4	60	5	1	2	SOD-323
BZT52C5V6S	200	5.6	5.2	6	40	5	3	2	SOD-323
BZT52C6V2S	200	6.2	5.8	6.6	10	5	2	4	SOD-323
BZT52C6V8S	200	6.8	6.4	7.2	15	5	1	4	SOD-323
BZT52C7V5S	200	7.5	7	7.9	15	5	0.7	5	SOD-323
BZT52C8V2S	200	8.2	7.7	8.7	15	5	0.2	5	SOD-323
BZT52C9V1S	200	9.1	8.5	9.6	15	5	0.2	6	SOD-323
BZT52C10S	200	10	9.4	10.6	15	5	0.1	7	SOD-323
BZT52C11S	200	11	10.4	11.6	15	5	0.1	8	SOD-323
BZT52C12S	200	12	11.4	12.7	25	5	0.1	8	SOD-323
BZT52C13S	200	13	12.4	14.1	30	5	0.1	8	SOD-323
BZT52C15S	200	15	13.8	15.6	30	5	0.1	10.5	SOD-323

DIODE List > ZenerDiode

BZT52C16S	200	16	15.3	17.1	40	5	0.1	11.2	SOD-323
BZT52C18S	200	18	16.8	19.1	45	5	0.1	12.6	SOD-323
BZT52C20S	200	20	18.8	21.2	55	5	0.1	14.4	SOD-323
BZT52C22S	200	22	20.8	23.3	55	5	0.1	16.4	SOD-323
BZT52C24S	200	24	22.8	25.6	70	5	0.1	18.4	SOD-323
BZT52C27S	200	27	25.1	28.9	80	2	0.1	21.4	SOD-323
BZT52C30S	200	30	28	32	80	2	0.1	24.4	SOD-323
BZT52C33S	200	33	31	35	80	2	0.1	27.4	SOD-323
BZT52C36S	200	36	34	38	90	2	0.1	30.4	SOD-323
BZT52C39S	200	39	37	41	130	2	0.1	33.4	SOD-323
UMMBZ5V6	300	5.6	5.32	5.88	11	20	5	3	SOT-23
UMMBZ6V2	300	6.2	5.89	6.51			0.5	3	SOT-23
UMMBZ9V1	300	9.1	8.65	9.56			0.3	6	SOT-23
UMMBZ10V	300	10	9.5	10.5			0.3	6.5	SOT-23
UMMBZ12V	300	12	11.4	12.6			200	8.5	SOT-23
UMMBZ15V	300	15	14.3	15.8			50	12.8	SOT-23
UMMBZ18V	300	18	17.1	18.9			50	14.5	SOT-23
UMMBZ20V	300	20	19	21			50	17	SOT-23
UMMBZ27V	300	27	25.65	28.35			50	22	SOT-23
UMMBZ33V	300	33	31.35	34.65			50	26	SOT-23
UMMBZ39V	300	39	37.05	40.95			50	31.2	SOT-23
BZT52C2V0S	410	2	1.91	2.09	100	5	150	1	SOT-23
BZT52C2V4S	410	2.4	2.2	2.6	100	5	50	1	SOT-23
BZT52C2V7S	410	2.7	2.5	2.9	100	5	20	1	SOT-23
BZT52C3S	410	3	2.8	3.2	100	5	10	1	SOT-23
BZT52C3V3S	410	3.3	3.1	3.5	95	5	5	1	SOT-23
BZT52C3V6S	410	3.6	3.4	3.8	95	5	5	1	SOT-23
BZT52C3V9S	410	3.9	3.7	4.1	90	5	3	1	SOT-23
BZT52C4V3S	410	4.3	4	4.6	90	5	3	1	SOT-23
BZT52C4V7S	410	4.7	4.4	5	90	5	2	2	SOT-23
BZT52C5V1S	410	5.1	4.8	5.4	60	5	1	2	SOT-23
BZT52C5V6S	410	5.6	5.2	6	40	5	3	2	SOT-23
BZT52C6V2S	410	6.2	5.8	6.6	10	5	2	4	SOT-23
BZT52C6V8S	410	6.8	6.4	7.2	15	5	1	4	SOT-23
BZT52C7V5S	410	7.5	7	7.9	15	5	0.7	5	SOT-23
BZT52C8V2S	410	8.2	7.7	8.7	15	5	0.2	5	SOT-23
BZT52C9V1S	410	9.1	8.5	9.6	15	5	0.2	6	SOT-23
BZT52C10S	410	10	9.4	10.6	15	5	0.1	7	SOT-23
BZT52C11S	410	11	10.4	11.6	15	5	0.1	8	SOT-23
BZT52C12S	410	12	11.4	12.7	25	5	0.1	8	SOT-23
BZT52C13S	410	13	12.4	14.1	30	5	0.1	8	SOT-23
BZT52C15S	410	15	13.8	15.6	30	5	0.1	10.5	SOT-23
BZT52C16S	410	16	15.3	17.1	40	5	0.1	11.2	SOT-23
BZT52C18S	410	18	16.8	19.1	45	5	0.1	12.6	SOT-23
BZT52C20S	410	20	18.8	21.2	55	5	0.1	14.4	SOT-23
BZT52C22S	410	22	20.8	23.3	55	5	0.1	16.4	SOT-23
BZT52C24S	410	24	22.8	25.6	70	5	0.1	18.4	SOT-23
BZT52C27S	410	27	25.1	28.9	80	2	0.1	21.4	SOT-23

DIODE List > ZenerDiode

BZT52C30S	410	30	28	32	80	2	0.1	24.4	SOT-23
BZT52C33S	410	33	31	35	80	2	0.1	27.4	SOT-23
BZT52C36S	410	36	34	38	90	2	0.1	30.4	SOT-23
BZT52C39S	410	39	37	41	130	2	0.1	33.4	SOT-23
MM1ZXX	350	30	28	32	80	2	0.1	23	SOT-23
DZ23C15	300	15	13.8	15.6	30	5	0.1	11	SOT-23
DZ23C22	300	22	20.8	23.3	55	5	0.1	17	SOT-23
DZ23C24	300	24	22.8	25.6	80	5	0.1	18	SOT-23
ZD7.5VS	225	7.5	7.29	7.71	6	20	3	6	SOT-23
ZD9.1VS	225	9.1	8.84	9.35	10	20	3	6.5	SOT-23
USMA5919	500	5.6	5.32	5.88	2	66.9	2.5	3	SMA
USMB5920	500	6.2	5.89	6.51	2	60.5	2.5	4	SMA
USMA5923	500	8.2	7.79	8.61	3.5	45.7	2.5	6.5	SMA
USMA5931	500	18	17.1	18.9	12	20.8	0.5	13.7	SMA
USMB5913	500	3.3	3.13	3.47	10	113.6	100	1	SMB
USMB5914	500	3.6	3.42	3.78	9	104.2	75	1	SMB
USMB5915	500	3.9	3.7	4.1	7.5	96.1	25	1	SMB
USMB5916	500	4.3	4.08	4.52	6	87.2	5	1	SMB
USMB5917	500	4.7	4.46	4.94	5	79.8	5	1.5	SMB
USMB5918	500	5.1	4.84	5.36	4	73.5	5	2	SMB
USMB5919	500	5.6	5.32	5.88	2	66.9	5	3	SMB
USMB5920	500	6.2	5.89	6.51	2	60.5	5	4	SMB
USMB5921	500	6.8	6.46	7.14	2.5	55.1	5	5.2	SMB
USMB5922	500	7.5	7.12	7.88	3	50	5	6	SMB
USMB5923	500	8.2	7.79	8.61	3.5	45.7	5	6.5	SMB
USMB5924	500	9.1	8.64	9.56	4	41.2	5	7	SMB
USMB5925	500	10	9.5	10.5	4.5	37.5	5	8	SMB
USMB5926	500	11	10.45	11.55	5.5	34.1	1	8.4	SMB
USMB5927	500	12	11.4	12.6	6.5	31.2	1	9.1	SMB
USMB5928	500	13	12.35	13.65	7	28.8	1	9.9	SMB
USMB5929	500	15	14.25	15.75	9	25	1	11.4	SMB
USMB5930	500	16	15.2	16.8	10	23.4	1	12.2	SMB
USMB5931	500	18	17.1	18.9	12	20.8	1	13.7	SMB
USMB5932	500	20	19	21	14	18.7	1	15.2	SMB
USMB5933	500	22	20.9	23.1	17.5	17	1	16.7	SMB
USMB5934	500	24	22.8	25.2	19	15.6	1	18.2	SMB
USMB5935	500	27	25.65	28.35	23	13.9	1	20.6	SMB
USMB5936	500	30	28.5	31.5	28	12.5	1	22.8	SMB
USMB5937	500	33	31.35	34.65	33	11.4	1	25.1	SMB
USMB5938	500	36	34.2	37.8	38	10.4	1	27.4	SMB
USMB5939	500	39	37.05	40.95	45	9.6	1	29.7	SMB
USMB5940	500	43	40.85	45.15	53	8.7	1	32.7	SMB
USMB5941	500	47	44.65	49.35	67	8	1	35.8	SMB
USMB5942	500	51	48.45	53.55	70	7.3	1	38.8	SMB
USMB5943	500	56	53.2	58.8	86	6.7	1	42.6	SMB
USMB5944	500	62	58.9	65.1	100	6	1	47.1	SMB
USMB5945	500	68	64.6	71.4	120	5.5	1	51.7	SMB
USMB5946	500	75	71.25	78.75	140	5	1	56	SMB
USMB5947	500	82	77.9	86.1	160	4.6	1	62.2	SMB
USMB5948	500	91	86.45	95.55	200	4.1	1	69.2	SMB
USMB5949	500	100	95	105	250	3.7	1	76	SMB
USMB5951	500	120	114	126	380	3.1	1	91.2	SMB
USMB5952	500	130	123.5	136.5	450	2.9	1	98.8	SMB

DIODE List > ZenerDiode

USMB5953	500	150	142.5	157.5	600	2.5	1	114	SMB
USMB5954	500	160	152	168	700	2.3	1	121.6	SMB
USMB5955	500	180	171	189	900	2.1	1	136.8	SMB
USMB5956	500	200	190	210	1200	1.9	1	152	SMB

DIODE List > Current Regulator Diode

PartNo. (勾选方式)	Peak Operating Voltage (V) (勾选方式)	Test Voltage (V) (勾选方式)	IP (mA)) Min (Range)	IP (mA)) Nom (Range)	IP (mA)) Max (Range)	VK (V)	@IK (IH)
UCR650-40	40.0	10.0	5.000	6.50	8.000	≤ 3.5	0.8
UCR1550-40	40.0	10.0	13.000	15.50	18.000	≤ 4	0.8
UCR100-70	70.0	10.0	0.800	1.00	1.200	≤ 2.5	0.8
UCR2050-70	70.0	10.0	17.000	20.50	24.000	≤ 4	0.8

Package
(勾选方式)

TO-92-2
SOD-123
SOT-89
TO-220
TO-251
TO-252
DO-41

~~DO-15~~
TO-92-2
SOD-123
SOT-89
TO-220
TO-251
TO-252
DO-41
~~DO-15~~

TO-92-2
SOD-123

TO-92-2
SOD-123

DIODE List > Diode Controller

PartNo. (每種方式)	DRAIN-BIAS Voltage (V)	SOURCE-DRAIN Voltage (V)	DRAIN-REF Voltage (V)	SOURCE Current (uA)	Turn-Off Differential Voltage (mV)Min.	Turn-Off Differential Voltage (mV)Max.	REF-SOURCE Voltage (VBIAS LOW) (mV)Min.	REF-SOURCE Voltage (VBIAS LOW) Test Conditions(uA)	REF-SOURCE Voltage (VBIAS HIGH) (mV)Max.	REF-SOURCE Voltage (VBIAS HIGH) Test Conditions(uA)	Package (每種方式)
UC396	40.0	50.0	0.595	6.70	5	80	300.0	10.0	800.0	100.0	SOT-363

PHOTOCOUPLER List > Photocoupler Transistor

PartNo. (勾選方式)	V _F (V) (MAX.)	I _R (μ A) (MAX.)	C _{IN} (pF) (MAX.)	I _{CEO} (nA) (MAX.)	BV _{CEO} (V) (MIN.) (勾選方式)	BV _{ECO} (V) (MIN.)	CTR % (MIN.)	CTR % (MAX.)	V _{CESAT} V (MAX.)
UPC816	1.4	10	250	100	80	6	50	600	0.2
UPC357	1.4	5	250	100	80	7	50	600	0.2
UPC817	1.4	10	250	100	35	6	50	600	0.2
UPC8171	1.4	10		100	350	6	20	300	0.3
UTC10XX*	1.4	10		100	80	7	50	500	0.3
UPC10XX	1.4	10.0		100	80	7	50	600	0.3

Package (勾選方式)
SMD-4 SMD-4C DIP-4 DIP-4C
SMD-4
SMD-4 DIP-4 DIP-4M DIP-4C
DIP-4
LSOP-4
LSOP-4

PHOTOCOUPLER List > PHOTO TRIAC

PartNo. (勾選方式)	IF(ON) (mA) MIN.	IF(ON) (mA) MAX.	V _F (V) (MAX.)	I _R (μ A) (MAX.)	V _{TM} (V) (MAX.)	IDRM (μ A) (MAX.)	VDRM (V) (MAX.) (勾選方式)	IH (mA) (MAX.) (勾選方式)	Pack (勾選)
UPT0133	-	10	1.4	10	3.0	100	600	25	DIP-8A SMD-8A
UPT3223	-	10	1.3	10	2.5	100	600	25	DIP-8A SMD-8A
UPT2223	-	10	1.3	10	2.5	100	600	25	DIP-8A SMD-8A
UPT1223	-	50	1.3	10	2.5	100	600	25	DIP-8A SMD-8A
UPT3082	-	10	1.5	10	2.5	100	800		DIP-4
UOC3020S	-	30	1.5	100	2.5	100	400		DIP-4
UOC3021S	-	15	1.5	100	2.5	100	400		DIP-4

TVS List > TVS>ESD TVS

PartNo. (有源方式)	MAX.Ratings PPK (8/20uS) (W)	MAX.Ratings IPP (8/20uS) (A) (Range)	ESD IEC61000-4- 2 KV(*MAX.) Contact (有源方式)	ESD IEC61000-4- 2 KV(*MAX.) Air (有源方式)	V _{nom} (V) (Range)	VBR MIN. (V) (Range)	VBR MAX. (V) (Range)	IR MAX. (uA)	IR Conditions VRWM(V)	VC(8/20uS) MAX.(V) TYP.	VC(8/20uS) Conditions IPP(A)	CJ(1/OtoGND. /IO) MAX.(pF)TYP. (Range)	CJ(1/OtoGN D./IO) VR/f(MHz)	Package (有源方式)
SMAXXV	50	5	+8KV	+15KV	3.3-36	4-40	-	0.15-20	3.3-36	10.9-55	1-8.8	20-100	0/1	SOD-123 SOD-323 SOD-523
SMDJXXX	3000 (10/1000us)	4.21-312.5	+8KV	+15KV	5~440	6.4-492	7.3-543	2	5-440	9.6-713	-	-	-	SMC
SMCJXXA	1500 (10/1000us)	4.41-156.25	+8KV	+15KV	5-190	6.4-211.28	7.3-258.4	1-800	5-190	9.6-340.1	4.41~156.25	-	-	SMC
SMCJXXCA	1500 (10/1000us)	2.1-163.04	+8KV	+15KV	5-440	6.4-492	7.3-543	1-800	5-440	9.2-713	2.1-163.04	-	-	SMC
UESD12VLIU	220	10	+30KV	+30KV	12	12.6	-	1	12	22	10	66	-	SOD-323
UESD12VNIU	4000	180	+30KV	+30KV	13.5	13.5	17.5	0.5	13.5	25	100	1000	-	DFN2018-6
ESD5V0L1B	-	2.5	+25KV	-	5	-	-	0.05	3	25	16 (t _p =30ns)	30	0/1	SOD-523
SOT05C	140	13	+8KV	+15KV	5	6	-	5	5	10	13	120	0/1	SOT-23
SLVU2.8	400	24	+8KV	+15KV	2.8	3	-	1	2.8	12.5	24	100	0/1	SOT-23
ESD3V3S2B	-	8	+8KV	+30KV	3.3	-	-	0.05	3.3	9	30 (t _p =100ns)	20	0/1	SOT-323
ESD6V2S1B	-	8	+30KV	-	6.2	-	-	0.1	6.2	14	30 (t _p =100ns)	10	0/1	SOT-323
UESD6V1N2U	235	18	+30KV	+30KV	6.1	6.1	7.2	20	5.25	16	15	105	0/1	SOT-23
UESDA6V1W5	150	-	+8KV	+15KV	3	6.1	7.2	1	3	-	-	90	0/1	SOT-353
UZ5C056	150	10	+8KV	+15KV	5	6.3	-	1	5	14.5	10	100	0/1	SOT-26
USMS05	350	24	+20KV	+25KV	5	6	-	20	5	14.5	24	400	0/1	SOT-26
UPRTR5V0U4D	-	-	+8KV	-	5.5	6	9	0.1	3	-	-	1	0/1	SOT-26
UESD4C5V6C08	-	5.5	+8KV	+15KV	5	6.2	-	2	5	10	5	1	-	SOT-23-5
PUSB220	-	-	+8KV	-	5.5	6	9	0.1	3	-	-	1	0/1	SOT-26
SRV05-4	350	12	+8KV	-	5	6	-	5	5	17	5	1.2	0/1	SOT-26
TVS45009	25	2.5	+8KV	+9KV	5.5	9	-	0.1	3.3	-	-	0.8	-	SOT-26
UESD4CUSB30	45	5	+8KV	+9KV	5.5	7	-	0.1	2.5	8	1	0.7	-	SOT-25
USB45012	60	3	+10KV	+10KV	-	6	-	0.5	2.5	-	-	1	-	SOT-26
CCVG7C5	0.75	-	+8KV	-	-	-	-	-	-	-	-	5	-	SSOP-16
USP720	-	-	+8KV	-	-	-	-	0.02	-	2	1	3	-	DIP-16
UESD3311	-	-	-	-	-	-	-	-	-	-	-	-	-	SC-59-3
UESD1CSV0	-	-	-	-	-	-	-	-	-	-	-	-	-	SOT-23
UESDCA5V6C09	-	-	-	-	-	-	-	-	-	-	-	-	-	SOT-23
UESD6C5V6C20	-	-	-	-	-	-	-	-	-	-	-	-	-	SOP8
UESDA5V6C06	-	-	-	-	-	-	-	-	-	-	-	-	-	SOT-23打靶6C06
UESDA5V6C10	-	-	-	-	-	-	-	-	-	-	-	-	-	SOT-23打靶6C10
UESDCA5V6C09	-	-	-	-	-	-	-	-	-	-	-	-	-	SOT-23打靶6C09
UTV52105	350	8	+30KV	+30KV	24	26.2	32	0.1	24	40	5	38	0/1	SOT-23
UESD5V0X1C30	350	20	+15KV	+30KV	5	6	-	1	5	21	20	30	0/1	SOD-323
UESD5V0X1C40	350	20	+15KV	+30KV	5	6	-	1	5	21	20	40	0/1	SOD-323
UESD5V0X1C50	350	20	+15KV	+30KV	5	6	-	1	5	21	20	50	0/1	SOD-323
UESD5V0L1B	350	7.5	+25KV	+25KV	5	5.6	7.6	1	5	12.8	7.5	20	0/1	SOD-323 X1DFN1006-2
UTV53105	350	8	+30KV	+30KV	32	35.6	-	0.1	32	59	5	30(typ)	0/1	SOT-23
UESD5V0LSU	66	10	+20KV	+25KV	5	5.7	7.5	1	5	8.2	5	66	0/1	SOT-363
UZ18C6V8	-	-	+8KV	-	-	6.4	7.2	2	5.25	11	2.5	120	0/1	SOP-20
UESD5V0S2U	400	47	+15KV	+30KV	5	6	7.3	1	5	21.5	47	500	0/1	SOT-23
UESDA6V1	300	15	+9KV	+25KV	3	6.1	7.2	1	3	12	15	105	0/1	SOT-26

TVS List > TVS>ESD TVS

USM712	150	7	±30KV	±30KV	7~12	7	12	0.5	7	15	7	85	0/1	SOT-23
--------	-----	---	-------	-------	------	---	----	-----	---	----	---	----	-----	--------

TVS List > ESD&EMI TVS

PartNo. (勾選方式)	PSS (W)	IPP (5/50nS) (A)	ESD IEC61000-4-2 KV(*M)	ESD IEC61000-4-2 KV(*M)	V _{RWM} (V) (勾選方式)	VBR MIN. (V) (勾選方式)	VBR MAX. (V)	IR MAX. (uA)	IR Condi tions VRWM(Resisto r RS(Ω) TYP.	Resisto r RPU(K Ω)	CJ(I/O toGND. /IO) MAX.(p	CJ(I/O toGND. /IO) /VR/f(M
URCZ1284-04	5	-	±8KV	-	5.5	6	-	10	5	33	-	-	-
URCZ1284-02	5	-	±8KV	-	5.5	6	-	10	5	33	-	-	-
VGA7S019	-	-	±8KV	±15KV	5	9	-	1	5	1	-	2.5	-
PPHDMI2020		-	±8KV	-	5	6	-	5	3.3	1.4	-	1.2	5/1

Package (勾选方式)
QSOP-28
QSOP-28
SSOP-16
SSOP-40

TVS List > Transient Voltage Suppressor

UNI (勾選方式)	BI (勾選方式)	WORKINGPEAKREVERSEVOLTAGEVRWM(V)	BREAKDOWNVOLTAGEVBR@ITMIN.(V)	BREAKDOWNVOLTAGEVBR@ITMAX.(V)	TestCurrentIT(mA)	MAXIMUMCLAMPINGVOLTAGEVC(V)@IPP	MAXIMUMREVERSECURRENTIP(A)	MAXIMUMREVERSELEAKAGEIR(μA)@VRWM
SMAJXX	SMAJXXC	5-440	6.4-492	7.3-543	10/1	9.6-713	41.67-0.56	800-1
SMAJXXA	SMAJXXCA	5-440	6.4-492	7-543	10/1	9.2-713	43.48-0.56	800-1
SMBJXXXA	SMBJXXXCA	5-450	6.4-492	7-543	10/1	9.2-713	65.22-0.84	1000-1
P6KEXXX	P6KEXXXC	5.5-487.2	6.12-540	7.48-660	10/1	10.8-864	55.56-0.69	1000-1
P6KEXXXA	P6KEXXXCA	5.8-513	6.46-570	7.14-630	10/1	10.5-828	57.14-0.72	1000-1
P6SMBXXXA	P6SMBXXXCA	5.8-513	6.46-570	7.14-630	10/1	10.5-828	57.14-0.72	1000-1
SMA6LXXA	-	5-85	6.4-94.4	7-104	10/1	9.2-137	65.3-4.4	800-1

Package (勾选方式)
SMA SOD-123
SMA SOD-123
SMB
DO-15
DO-15
SMB
SMAF

TVS List > TVS DIODE FOR ESD PROTECTION

PartNo. (勾选方式)	V_{RWM} (V) (Typ)	Reverse Breakdown Voltage V_{BR} (V)	I_T (mA)	ReverseLeakage CurrentIR (uA)	V_R (V)	ESDVoltage	ClampingV oltage (tp=8/20μs) VC	ClampingV oltage (tp=8/20μs) IPP
USDXXW	3.3-36	4-40	1	125-1	3.3-36	25	6.5-60	1

Package
(勾选方式)

SOD-123
SOD-323